Conversion from Coleman Mach to Honeywell RTH 111 Thermostat

type rocker switch for Green – AC Fan High Speed fan speed control, I'd Green – AC Fan High Speed Gray – AC Fan Low Speed Gray – AC Fan Low Speed suggest a JR Products model # 12625. White – To Furnace White – To Furnace Yellow – To AC Yellow – To AC Red - + 12VDCRed - + 12VDCBlue - Ground Blue - Ground Honeywell Coleman Mach **RTH111 Analog** Digital Thermostat **Thermostat** RC R Υ R W Not Used GL W GW Υ Blue not used; RTH 111 is battery powered, no ground required В G 0 The thermostat is basically a В switch that connects the red +12 VDC power to all of the other connections. If not battery powered, then a ground is required. Low

SPDT switch added to T-stat for fan speed control*

High

If you want to use an RV

^{*}If you don't want to add the switch, just pick a speed wire and attach it to the G connection.